



(in delivery not included)

## **BTWL-MELODIE-230VAC** Radio controlled signaller

- + To be used for break-, fire alarm- or similar signalling in schools, industrial factories, official buildings and so on
- + Wireless control via radio transmission from master clock of series BT
- + Efficient, integrated 5 W booster with volume adjustment
- + 3 buttons for individual adjustment:
  - + Selection of melody
  - + Adjustment of volume
  - + Testing mode
- + 16 pre-programmed, stored melodies
- + Two-digit, green LED 7-segment-display of activated melody number
- + Radio channel via slide switches selectable
- + SD card slot for input of customer specific melodies (digital audio files MP3) via SD card (the SD card must be formatted with FAT16), or e.g. storage of an announcement
- + Melody duration depends on file size
- + To be used indoors

### **Technical data:**

|                        |                            |
|------------------------|----------------------------|
| Loudspeaker size:      | Ø 100 mm                   |
| Sound volume:          | max. 90 dB/A               |
| Protection class:      | IP 31                      |
| Power supply:          | 100 ... 240 V AC, 50/60 Hz |
| Power consumption:     | 6 VA                       |
| Operating temperature: | 0 °C ... +50 °C            |
| Dimensions (WxHxD):    | 150 x 202 x 43 mm          |
| Weight:                | 1 kg                       |

### **Mounting**

White ABS plastic case for wall mounting indoors

### **Option**

BTWL-MELODIE-24VDC    Wireless version with 24 V DC power supply



MATTIG



WENZEL



NEUMANN